

V7-RUB6

V7 Option Switch Settings: 1 (Pulse/ICT004/MDB)

Supported bill Ruble 50, 100, 200, 500, 1000, 2000 6bills.

V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Ruble 50	ON											
★	Accept Ruble 50	OFF											
★	Reject Ruble 100		ON										
★	Accept Ruble 100		OFF										
★	Reject Ruble 200			ON									
★	Accept Ruble 200			OFF									
★	Reject Ruble 500				ON								
★	Accept Ruble 500				OFF								
★	Reject Ruble 1000 & 2000				ON								
★	Accept Ruble 1000 & 2000				OFF								
★	Reserved				ON								
★	Reserved				OFF								
★	Harness Disable					ON							
★	Harness Enable					OFF							
★	Inhibit Active High						ON						
★	Inhibit Active Low						OFF						
★	1 pulse / Ruble 50							OFF	OFF				
★	2 pulses / Ruble 50							ON	OFF				
★	5 pulses / Ruble 50							OFF	ON				
★	50 pulses / Ruble 50							ON	ON				
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

◆ Factory configuration has all switches in the OFF position.

Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)

V7-RUB6(Pulse/ICT004/MDB)

V7 Interface Settings: 3 (ICT004)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
★	Reserved	OFF			
★	Pulse Mode		ON	OFF	
★	MDB Interface		OFF	OFF	
★	ICT004 Interface		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

V7 Interface Settings: 3 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
★	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
★	MDB Interface		OFF	OFF	
★	ICT004 Interface		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

V7 Interface Settings: 3 (MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
★	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★	Pulse Mode		ON	OFF	
★	MDB Interface		OFF	OFF	
★	ICT004 Interface		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT004	Pulse	MDB
BV1			
BV2	Ruble 50	Ruble 50	Ruble 50
BV3	Ruble 100	Ruble 100	Ruble 100
BV4	Ruble 500	Ruble 500	Ruble 500
BV5	Ruble 1000	Ruble 1000	Ruble 1000
BV6	Ruble 200	Ruble 200	Ruble 200
BV7	Ruble 2000	Ruble 2000	Ruble 2000